

DMX CHARTS

RDM Model ID	HEX	DEC
ECLCTPLUSHP	A036	41014
ECLCTPLUSHIP	A037	41015

DMX MODES

Ch	UNO	DUO	IRGB	STANDARD	EXTENDED (Legacy)	M2 - CCT 16bit	M4 - RGB 16 bit
1	Dimmer	Dimmer	Dimmer	Dimmer	Dimmer	Dimmer	Dimmer
2	Gobo Rot	Dimmer Fine	Red	Dimmer Fine	Dimmer Fine	Dimmer Fine	Dimmer Fine
3	Gobo Rot Fine	Gobo Rot	Green	CCT	Strobe	CCT	Red
4		Gobo Rot Fine	Blue	CCT fine	CCT	CCT Fine	Red Fine
5			Gobo Rot	GMP	GMP	GMP	Green
6			Gobo Rot Fine	Crossfade CCT to RGB	Red	CCT Range Selector	Green Fine
7				Red	Green	Strobe	Blue
8				Green	Blue	Control	Blue Fine
9				Blue	Colour Macro	Preset	White Point
10				Strobe	Colour Macro Saturation	Fan Control	White Point Fine
11				Control	Reserved	Reserved	Strobe
12				Gobo Rot	Control	Gobo Rot	Control
13				Gobo Rot Fine	Gobo Rot	Gobo Rot Fine	Preset
14					Gobo Rot Fine		Fan Control
15							Reserved
16							Gobo Rot
17							Gobo Rot Fine

NOTE:

CCT channel refers to 2800K - 10000K when the CCT range selector channel is not available.

DMX MODES

Ch	M8 - XY 16 bit	M16 - CCT + RGB 16 bit	M18 - CCT + RGB 16 bit + GEL 16 bit	M28 - CCT + XY 16 bit	M30 - CCT + XY + GEL 16 bit	M36 - RAW 16 bit	M37 - CCT + RAW 16 bit
1	Dimmer	Dimmer	Dimmer	Dimmer	Dimmer	Dimmer	Dimmer
2	Dimmer Fine	Dimmer Fine	Dimmer Fine	Dimmer Fine	Dimmer Fine	Dimmer Fine	Dimmer Fine
3	X1	CCT	CCT	CCT	CCT	Red	CCT
4	X1 fine	CCT Fine	CCT Fine	CCT Fine	CCT Fine	Red Fine	CCT Fine
5	Y1	GMP	GMP	GMP	GMP	Green	GMP
6	Y1 fine	Crossfade from CCT to RGB	Crossfade from CCT to RGB	Crossfade from CCT to XY	Crossfade from CCT to XY	Green Fine	Crossfade from CCT to RAW
7	Crossfade XY1 to XY2	Red	Red	X	X	Blue	Red
8	X2	Red Fine	Red Fine	X Fine	X Fine	Blue Fine	Red Fine
9	X2 fine	Green	Green	Y	Y	PC Amber	Green
10	Y2	Green Fine	Green Fine	Y Fine	Y Fine	PC Amber Fine	Green Fine
11	Y2 fine	Blue	Blue	CCT Range Selector	Crossfade from XY to GEL	Mint	Blue
12	Transition Type	Blue Fine	Blue Fine	Transition Type	GEL Source Selector	Mint Fine	Blue Fine
13	Strobe	CCT Range Selector	Crossfade from RGB to GEL	Strobe	GEL Brand / Category	Royal Blue	PC Amber
14	Control	White Point	GEL Source Selector	Control	GEL Selector	Royal Blue Fine	PC Amber Fine
15	Preset	White Point Fine	GEL Brand / Category	Preset	CCT Range Selector	Strobe	Mint
16	Fan Control	Transition Type	GEL Selector	Fan Control	Transition Type	Control	Mint Fine
17	Reserved	Strobe	CCT Range Selector	Reserved	Strobe	Preset	Royal Blue
18	Gobo Rot	Control	White Point	Gobo Rot	Control	Fan Control	Royal Blue Fine
19	Gobo Rot Fine	Preset	White Point Fine	Gobo Rot Fine	Preset	Reserved	Strobe
20		Fan Control	Transition Type		Fan Control	Gobo Rot	CCT Range Selector
21		Reserved	Strobe		Reserved	Gobo Rot Fine	Transition Type
22		Gobo Rot	Control		Gobo Rot		Control
23		Gobo Rot Fine	Preset		Gobo Rot Fine		Preset
24			Fan Control				Fan Control
25			Reserved				Reserved
26			Gobo Rot				Gobo Rot
27			Gobo Rot Fine				Gobo Rot Fine

DMX MODES

Ch	M38 - CCT + GEL 16 bit + RAW 16 bit	M4 - RGB 16 bit + CC	M8 - XY 16 bit + CC	M16 - CC - CCT + RGB 16 bit	M18 - CC - CCT + RGB 16 bit + GEL 16 bit	M28 - CC - CCT + XY 16 bit	M30 - CC - CCT + XY + GEL 16 bit
1	Dimmer	Dimmer	Dimmer	Dimmer	Dimmer	Dimmer	Dimmer
2	Dimmer Fine	Dimmer Fine	Dimmer Fine	Dimmer Fine	Dimmer Fine	Dimmer Fine	Dimmer Fine
3	CCT	Red	X1	CCT	CCT	CCT	CCT
4	CCT Fine	Red Fine	X1 fine	CCT Fine	CCT Fine	CCT Fine	CCT Fine
5	GMP	Green	Y1	GMP	GMP	GMP	GMP
6	Crossfade from CCT to GEL	Green Fine	Y1 fine	Crossfade from CCT to RGB	Crossfade from CCT to RGB	Crossfade from CCT to XY	Crossfade from CCT to XY
7	GEL Source Selector	Blue	Crossfade XY1 to XY2	Red	Red	X	X
8	GEL Brand / Category	Blue Fine	X2	Red Fine	Red Fine	X Fine	X Fine
9	GEL Selector	White Point	X2 fine	Green	Green	Y	Y
10	Crossfade from GEL to RAW	White Point Fine	Y2	Green Fine	Green Fine	Y Fine	Y Fine
11	Red	Strobe	Y2 fine	Blue	Blue	CCT Range Selector	Crossfade from XY to GEL
12	Red Fine	Control	Transition Type	Blue Fine	Blue Fine	Transition Type	GEL Source Selector
13	Green	Preset	Strobe	CCT Range Selector	Crossfade from RGB to GEL	Strobe	GEL Brand / Category
14	Green Fine	Fan Control	Control	White Point	GEL Source Selector	Control	GEL Selector
15	Blue	Reserved	Preset	White Point Fine	GEL Brand / Category	Preset	CCT Range Selector
16	Blue Fine	CC Mode	Fan Control	Transition Type	GEL Selector	Fan Control	Transition Type
17	PC Amber	Warmer / Cooler	Reserved	Strobe	CCT Range Selector	Reserved	Strobe
18	PC Amber Fine	Saturate / Desaturate	CC Mode	Control	White Point	CC Mode	Control
19	Mint	Red	Warmer / Cooler	Preset	White Point Fine	Warmer / Cooler	Preset
20	Mint Fine	Green	Saturate / Desaturate	Fan Control	Transition Type	Saturate / Desaturate	Fan Control
21	Royal Blue	Blue	Red	Reserved	Strobe	Red	Reserved
22	Royal Blue Fine	PC Amber	Green	CC Mode	Control	Green	CC Mode
23	Strobe	Mint	Blue	Warmer / Cooler	Preset	Blue	Warmer / Cooler
24	CCT Range Selector	Royal Blue	PC Amber	Saturate / Desaturate	Fan Control	PC Amber	Saturate / Desaturate
25	Transition Type	Gobo Rot	Mint	Red	Reserved	Mint	Red
26	Control	Gobo Rot Fine	Royal Blue	Green	CC Mode	Royal Blue	Green
27	Preset		Gobo Rot	Blue	Warmer / Cooler	Gobo Rot	Blue
28	Fan Control		Gobo Rot Fine	PC Amber	Saturate / Desaturate	Gobo Rot Fine	PC Amber
29	Reserved			Mint	Red		Mint
30	Gobo Rot			Royal Blue	Green		Royal Blue
31	Gobo Rot Fine			Gobo Rot	Blue		Gobo Rot
32				Gobo Rot Fine	PC Amber		Gobo Rot Fine
33					Mint		
34					Royal Blue		
35					Gobo Rot		
36					Gobo Rot Fine		

CHANNEL DEFINITION

Dimmer					
Function	8 bit value		16 bit value		Note
	From	To	From	To	
Dimmer	0	255	0	65535	Default @ 0 (Linear Dimmer 0 - 100%)

CCT Range Selector						
Function		8 bit value		16 bit value		Note
		From	To	From	To	
CCT(K) From	CCT(K) To					Default @ 0 (Linear from 1850K to 20000K)
1850K	20000K	0	9	-	-	
2200K	15000K	10	19	-	-	
2800K	10000K	20	29	-	-	
2200K	20000K	30	39	-	-	
Reserved		40	255	-	-	

CCT (When CCT Range Selector @ 1850K - 20000K)						
Function		8 bit value		16 bit value		Note
		From	To	From	To	
CCT(K) From	CCT(K) To					Default @ 0
1850	1900	0	1	0	181	
1900	2000	1	2	181	542	
2000	2100	2	4	542	903	
2100	2200	4	5	903	1264	
2200	2300	5	6	1264	1625	
2300	2400	6	8	1625	1986	
2400	2500	8	9	1986	2347	
2500	2600	9	11	2347	2708	
2600	2700	11	12	2708	3069	
2700	2800	12	13	3069	3430	
2800	2900	13	15	3430	3791	
2900	3000	15	16	3791	4152	
3000	3100	16	18	4152	4513	
3100	3200	18	19	4513	4875	
3200	3300	19	20	4875	5236	
3300	3400	20	22	5236	5597	
3400	3500	22	23	5597	5958	
3500	3600	23	25	5958	6319	
3600	3700	25	26	6319	6680	
3700	3800	26	27	6680	7041	
3800	3900	27	29	7041	7402	
3900	4000	29	30	7402	7763	
4000	4100	30	32	7763	8124	
4100	4200	32	33	8124	8485	
4200	4300	33	34	8485	8846	
4300	4400	34	36	8846	9207	
4400	4500	36	37	9207	9568	
4500	4600	37	39	9568	9930	
4600	4700	39	40	9930	10291	
4700	4800	40	41	10291	10652	
4800	4900	41	43	10652	11013	
4900	5000	43	44	11013	11374	

CCT (When CCT Range Selector @ 1850K - 20000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
5000	5100	44	46	11374	11735	
5100	5200	46	47	11735	12096	
5200	5300	47	48	12096	12457	
5300	5400	48	50	12457	12818	
5400	5500	50	51	12818	13179	
5500	5600	51	53	13179	13540	
5600	5700	53	54	13540	13901	
5700	5800	54	55	13901	14262	
5800	5900	55	57	14262	14624	
5900	6000	57	58	14624	14985	
6000	6100	58	60	14985	15346	
6100	6200	60	61	15346	15707	
6200	6300	61	63	15707	16068	
6300	6400	63	64	16068	16429	
6400	6500	64	65	16429	16790	
6500	6600	65	67	16790	17151	
6600	6700	67	68	17151	17512	
6700	6800	68	70	17512	17873	
6800	6900	70	71	17873	18234	
6900	7000	71	72	18234	18595	
7000	7100	72	74	18595	18956	
7100	7200	74	75	18956	19317	
7200	7300	75	77	19317	19679	
7300	7400	77	78	19679	20040	
7400	7500	78	79	20040	20401	
7500	7600	79	81	20401	20762	
7600	7700	81	82	20762	21123	
7700	7800	82	84	21123	21484	
7800	7900	84	85	21484	21845	
7900	8000	85	86	21845	22206	
8000	8100	86	88	22206	22567	
8100	8200	88	89	22567	22928	
8200	8300	89	91	22928	23289	
8300	8400	91	92	23289	23650	
8400	8500	92	93	23650	24011	
8500	8600	93	95	24011	24373	
8600	8700	95	96	24373	24734	
8700	8800	96	98	24734	25095	
8800	8900	98	99	25095	25456	
8900	9000	99	100	25456	25817	
9000	9100	100	102	25817	26178	
9100	9200	102	103	26178	26539	
9200	9300	103	105	26539	26900	
9300	9400	105	106	26900	27261	
9400	9500	106	107	27261	27622	
9500	9600	107	109	27622	27983	
9600	9700	109	110	27983	28344	
9700	9800	110	112	28344	28705	
9800	9900	112	113	28705	29066	
9900	10000	113	115	29066	29428	

CCT (When CCT Range Selector @ 1850K - 20000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
10000	10100	115	116	29428	29789	
10100	10200	116	117	29789	30150	
10200	10300	117	119	30150	30511	
10300	10400	119	120	30511	30872	
10400	10500	120	122	30872	31233	
10500	10600	122	123	31233	31594	
10600	10700	123	124	31594	31955	
10700	10800	124	126	31955	32316	
10800	10900	126	127	32316	32677	
10900	11000	127	129	32677	33038	
11000	11100	129	130	33038	33399	
11100	11200	130	131	33399	33760	
11200	11300	131	133	33760	34122	
11300	11400	133	134	34122	34483	
11400	11500	134	136	34483	34844	
11500	11600	136	137	34844	35205	
11600	11700	137	138	35205	35566	
11700	11800	138	140	35566	35927	
11800	11900	140	141	35927	36288	
11900	12000	141	143	36288	36649	
12000	12100	143	144	36649	37010	
12100	12200	144	145	37010	37371	
12200	12300	145	147	37371	37732	
12300	12400	147	148	37732	38093	
12400	12500	148	150	38093	38454	
12500	12600	150	151	38454	38815	
12600	12700	151	152	38815	39177	
12700	12800	152	154	39177	39538	
12800	12900	154	155	39538	39899	
12900	13000	155	157	39899	40260	
13000	13100	157	158	40260	40621	
13100	13200	158	159	40621	40982	
13200	13300	159	161	40982	41343	
13300	13400	161	162	41343	41704	
13400	13500	162	164	41704	42065	
13500	13600	164	165	42065	42426	
13600	13700	165	166	42426	42787	
13700	13800	166	168	42787	43148	
13800	13900	168	169	43148	43509	
13900	14000	169	171	43509	43871	
14000	14100	171	172	43871	44232	
14100	14200	172	174	44232	44593	
14200	14300	174	175	44593	44954	
14300	14400	175	176	44954	45315	
14400	14500	176	178	45315	45676	
14500	14600	178	179	45676	46037	
14600	14700	179	181	46037	46398	
14700	14800	181	182	46398	46759	
14800	14900	182	183	46759	47120	
14900	15000	183	185	47120	47481	

CCT (When CCT Range Selector @ 1850K - 20000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
15000	15100	185	186	47481	47842	
15100	15200	186	188	47842	48203	
15200	15300	188	189	48203	48565	
15300	15400	189	190	48565	48926	
15400	15500	190	192	48926	49287	
15500	15600	192	193	49287	49648	
15600	15700	193	195	49648	50009	
15700	15800	195	196	50009	50370	
15800	15900	196	197	50370	50731	
15900	16000	197	199	50731	51092	
16000	16100	199	200	51092	51453	
16100	16200	200	202	51453	51814	
16200	16300	202	203	51814	52175	
16300	16400	203	204	52175	52536	
16400	16500	204	206	52536	52897	
16500	16600	206	207	52897	53258	
16600	16700	207	209	53258	53620	
16700	16800	209	210	53620	53981	
16800	16900	210	211	53981	54342	
16900	17000	211	213	54342	54703	
17000	17100	213	214	54703	55064	
17100	17200	214	216	55064	55425	
17200	17300	216	217	55425	55786	
17300	17400	217	218	55786	56147	
17400	17500	218	220	56147	56508	
17500	17600	220	221	56508	56869	
17600	17700	221	223	56869	57230	
17700	17800	223	224	57230	57591	
17800	17900	224	225	57591	57952	
17900	18000	225	227	57952	58314	
18000	18100	227	228	58314	58675	
18100	18200	228	230	58675	59036	
18200	18300	230	231	59036	59397	
18300	18400	231	233	59397	59758	
18400	18500	233	234	59758	60119	
18500	18600	234	235	60119	60480	
18600	18700	235	237	60480	60841	
18700	18800	237	238	60841	61202	
18800	18900	238	240	61202	61563	
18900	19000	240	241	61563	61924	
19000	19100	241	242	61924	62285	
19100	19200	242	244	62285	62646	
19200	19300	244	245	62646	63007	
19300	19400	245	247	63007	63369	
19400	19500	247	248	63369	63730	
19500	19600	248	249	63730	64091	
19600	19700	249	251	64091	64452	
19700	19800	251	252	64452	64813	
19800	19900	252	254	64813	65174	
19900	20000	254	255	65174	65535	

CCT (When CCT Range Selector @ 2200K - 15000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
2200	2300	0	2	0	512	Default @ 0
2300	2400	2	4	512	1024	
2400	2500	4	6	1024	1536	
2500	2600	6	8	1536	2048	
2600	2700	8	10	2048	2560	
2700	2800	10	12	2560	3072	
2800	2900	12	14	3072	3584	
2900	3000	14	16	3584	4096	
3000	3100	16	18	4096	4608	
3100	3200	18	20	4608	5120	
3200	3300	20	22	5120	5632	
3300	3400	22	24	5632	6144	
3400	3500	24	26	6144	6656	
3500	3600	26	28	6656	7168	
3600	3700	28	30	7168	7680	
3700	3800	30	32	7680	8192	
3800	3900	32	34	8192	8704	
3900	4000	34	36	8704	9216	
4000	4100	36	38	9216	9728	
4100	4200	38	40	9728	10240	
4200	4300	40	42	10240	10752	
4300	4400	42	44	10752	11264	
4400	4500	44	46	11264	11776	
4500	4600	46	48	11776	12288	
4600	4700	48	50	12288	12800	
4700	4800	50	52	12800	13312	
4800	4900	52	54	13312	13824	
4900	5000	54	56	13824	14336	
5000	5100	56	58	14336	14848	
5100	5200	58	60	14848	15360	
5200	5300	60	62	15360	15872	
5300	5400	62	64	15872	16384	
5400	5500	64	66	16384	16896	
5500	5600	66	68	16896	17408	
5600	5700	68	70	17408	17920	
5700	5800	70	72	17920	18432	
5800	5900	72	74	18432	18944	
5900	6000	74	76	18944	19456	
6000	6100	76	78	19456	19968	
6100	6200	78	80	19968	20480	
6200	6300	80	82	20480	20992	
6300	6400	82	84	20992	21504	
6400	6500	84	86	21504	22016	
6500	6600	86	88	22016	22528	
6600	6700	88	90	22528	23040	
6700	6800	90	92	23040	23552	
6800	6900	92	94	23552	24064	
6900	7000	94	96	24064	24576	
7000	7100	96	98	24576	25088	
7100	7200	98	100	25088	25600	

CCT (When CCT Range Selector @ 2200K - 15000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
7200	7300	100	102	25600	26112	
7300	7400	102	104	26112	26624	
7400	7500	104	106	26624	27136	
7500	7600	106	108	27136	27648	
7600	7700	108	110	27648	28160	
7700	7800	110	112	28160	28672	
7800	7900	112	114	28672	29184	
7900	8000	114	116	29184	29696	
8000	8100	116	118	29696	30208	
8100	8200	118	120	30208	30720	
8200	8300	120	122	30720	31232	
8300	8400	122	124	31232	31744	
8400	8500	124	126	31744	32256	
8500	8600	126	128	32256	32768	
8600	8700	128	129	32768	33279	
8700	8800	129	131	33279	33791	
8800	8900	131	133	33791	34303	
8900	9000	133	135	34303	34815	
9000	9100	135	137	34815	35327	
9100	9200	137	139	35327	35839	
9200	9300	139	141	35839	36351	
9300	9400	141	143	36351	36863	
9400	9500	143	145	36863	37375	
9500	9600	145	147	37375	37887	
9600	9700	147	149	37887	38399	
9700	9800	149	151	38399	38911	
9800	9900	151	153	38911	39423	
9900	10000	153	155	39423	39935	
10000	10100	155	157	39935	40447	
10100	10200	157	159	40447	40959	
10200	10300	159	161	40959	41471	
10300	10400	161	163	41471	41983	
10400	10500	163	165	41983	42495	
10500	10600	165	167	42495	43007	
10600	10700	167	169	43007	43519	
10700	10800	169	171	43519	44031	
10800	10900	171	173	44031	44543	
10900	11000	173	175	44543	45055	
11000	11100	175	177	45055	45567	
11100	11200	177	179	45567	46079	
11200	11300	179	181	46079	46591	
11300	11400	181	183	46591	47103	
11400	11500	183	185	47103	47615	
11500	11600	185	187	47615	48127	
11600	11700	187	189	48127	48639	
11700	11800	189	191	48639	49151	
11800	11900	191	193	49151	49663	
11900	12000	193	195	49663	50175	
12000	12100	195	197	50175	50687	
12100	12200	197	199	50687	51199	

CCT (When CCT Range Selector @ 2200K - 15000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
12200	12300	199	201	51199	51711	
12300	12400	201	203	51711	52223	
12400	12500	203	205	52223	52735	
12500	12600	205	207	52735	53247	
12600	12700	207	209	53247	53759	
12700	12800	209	211	53759	54271	
12800	12900	211	213	54271	54783	
12900	13000	213	215	54783	55295	
13000	13100	215	217	55295	55807	
13100	13200	217	219	55807	56319	
13200	13300	219	221	56319	56831	
13300	13400	221	223	56831	57343	
13400	13500	223	225	57343	57855	
13500	13600	225	227	57855	58367	
13600	13700	227	229	58367	58879	
13700	13800	229	231	58879	59391	
13800	13900	231	233	59391	59903	
13900	14000	233	235	59903	60415	
14000	14100	235	237	60415	60927	
14100	14200	237	239	60927	61439	
14200	14300	239	241	61439	61951	
14300	14400	241	243	61951	62463	
14400	14500	243	245	62463	62975	
14500	14600	245	247	62975	63487	
14600	14700	247	249	63487	63999	
14700	14800	249	251	63999	64511	
14800	14900	251	253	64511	65023	
14900	15000	253	255	65023	65535	

CCT (When CCT Range Selector @ 2800K - 10000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
2800	2900	0	4	0	910	Default @ 0
2900	3000	4	7	910	1820	
3000	3100	7	11	1820	2731	
3100	3200	11	14	2731	3641	
3200	3300	14	18	3641	4551	
3300	3400	18	21	4551	5461	
3400	3500	21	25	5461	6371	
3500	3600	25	28	6371	7282	
3600	3700	28	32	7282	8192	
3700	3800	32	35	8192	9102	
3800	3900	35	39	9102	10012	
3900	4000	39	43	10012	10923	
4000	4100	43	46	10923	11833	
4100	4200	46	50	11833	12743	
4200	4300	50	53	12743	13653	
4300	4400	53	57	13653	14563	
4400	4500	57	60	14563	15474	
4500	4600	60	64	15474	16384	
4600	4700	64	67	16384	17294	
4700	4800	67	71	17294	18204	
4800	4900	71	74	18204	19114	
4900	5000	74	78	19114	20025	
5000	5100	78	81	20025	20935	
5100	5200	81	85	20935	21845	
5200	5300	85	89	21845	22755	
5300	5400	89	92	22755	23665	
5400	5500	92	96	23665	24576	
5500	5600	96	99	24576	25486	
5600	5700	99	103	25486	26396	
5700	5800	103	106	26396	27306	
5800	5900	106	110	27306	28216	
5900	6000	110	113	28216	29127	
6000	6100	113	117	29127	30037	
6100	6200	117	120	30037	30947	
6200	6300	120	124	30947	31857	
6300	6400	124	128	31857	32768	
6400	6500	128	131	32768	33678	
6500	6600	131	135	33678	34588	
6600	6700	135	138	34588	35498	
6700	6800	138	142	35498	36408	
6800	6900	142	145	36408	37319	
6900	7000	145	149	37319	38229	
7000	7100	149	152	38229	39139	
7100	7200	152	156	39139	40049	
7200	7300	156	159	40049	40959	
7300	7400	159	163	40959	41870	
7400	7500	163	166	41870	42780	
7500	7600	166	170	42780	43690	
7600	7700	170	174	43690	44600	
7700	7800	174	177	44600	45510	

CCT (When CCT Range Selector @ 2800K - 10000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
7800	7900	177	181	45510	46421	
7900	8000	181	184	46421	47331	
8000	8100	184	188	47331	48241	
8100	8200	188	191	48241	49151	
8200	8300	191	195	49151	50061	
8300	8400	195	198	50061	50972	
8400	8500	198	202	50972	51882	
8500	8600	202	205	51882	52792	
8600	8700	205	209	52792	53702	
8700	8800	209	213	53702	54613	
8800	8900	213	216	54613	55523	
8900	9000	216	220	55523	56433	
9000	9100	220	223	56433	57343	
9100	9200	223	227	57343	58253	
9200	9300	227	230	58253	59164	
9300	9400	230	234	59164	60074	
9400	9500	234	237	60074	60984	
9500	9600	237	241	60984	61894	
9600	9700	241	244	61894	62804	
9700	9800	244	248	62804	63715	
9800	9900	248	251	63715	64625	
9900	10000	251	255	64625	65535	

CCT (When CCT Range Selector @ 2200K - 20000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
2200	2216	0	1	0	59	Default @ 0
2216	2232	1	2	59	118	
2232	2248	2	3	118	177	
2248	2264	3	4	177	236	
2264	2281	4	5	236	298	
2281	2297	5	6	298	357	
2297	2314	6	7	357	420	
2314	2331	7	8	420	482	
2331	2348	8	9	482	545	
2348	2365	9	10	545	607	
2365	2382	10	11	607	670	
2382	2399	11	12	670	733	
2399	2417	12	13	733	799	
2417	2434	13	14	799	862	
2434	2452	14	15	862	928	
2452	2469	15	16	928	990	
2469	2487	16	17	990	1057	
2487	2505	17	18	1057	1123	
2505	2524	18	19	1123	1193	
2524	2542	19	20	1193	1259	
2542	2560	20	21	1259	1325	
2560	2579	21	22	1325	1395	
2579	2598	22	23	1395	1465	
2598	2616	23	24	1465	1532	
2616	2635	24	25	1532	1602	
2635	2654	25	26	1602	1672	
2654	2674	26	27	1672	1745	
2674	2693	27	28	1745	1815	
2693	2713	28	29	1815	1889	
2713	2732	29	30	1889	1959	
2732	2752	30	31	1959	2032	
2752	2772	31	32	2032	2106	
2772	2792	32	33	2106	2180	
2792	2812	33	34	2180	2253	
2812	2833	34	35	2253	2331	
2833	2853	35	36	2331	2404	
2853	2874	36	37	2404	2481	
2874	2895	37	38	2481	2559	
2895	2916	38	39	2559	2636	
2916	2937	39	40	2636	2713	
2937	2958	40	41	2713	2791	
2958	2980	41	42	2791	2872	
2980	3001	42	43	2872	2949	
3001	3023	43	44	2949	3030	
3023	3045	44	45	3030	3111	
3045	3067	45	46	3111	3192	
3067	3089	46	47	3192	3273	
3089	3112	47	48	3273	3358	
3112	3134	48	49	3358	3439	
3134	3157	49	50	3439	3523	

CCT (When CCT Range Selector @ 2200K - 20000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
3157	3180	50	51	3523	3608	
3180	3203	51	52	3608	3693	
3203	3226	52	53	3693	3777	
3226	3249	53	54	3777	3862	
3249	3273	54	55	3862	3951	
3273	3297	55	56	3951	4039	
3297	3321	56	57	4039	4127	
3321	3345	57	58	4127	4216	
3345	3369	58	59	4216	4304	
3369	3393	59	60	4304	4392	
3393	3418	60	61	4392	4484	
3418	3443	61	62	4484	4576	
3443	3468	62	63	4576	4668	
3468	3493	63	64	4668	4760	
3493	3518	64	65	4760	4853	
3518	3544	65	66	4853	4948	
3544	3569	66	67	4948	5040	
3569	3595	67	68	5040	5136	
3595	3621	68	69	5136	5232	
3621	3647	69	70	5232	5327	
3647	3674	70	71	5327	5427	
3674	3700	71	72	5427	5523	
3700	3727	72	73	5523	5622	
3727	3754	73	74	5622	5721	
3754	3782	74	75	5721	5825	
3782	3809	75	76	5825	5924	
3809	3837	76	77	5924	6027	
3837	3864	77	78	6027	6126	
3864	3892	78	79	6126	6230	
3892	3921	79	80	6230	6336	
3921	3949	80	81	6336	6439	
3949	3978	81	82	6439	6546	
3978	4006	82	83	6546	6649	
4006	4036	83	84	6649	6760	
4036	4065	84	85	6760	6866	
4065	4094	85	86	6866	6973	
4094	4124	86	87	6973	7084	
4124	4154	87	88	7084	7194	
4154	4184	88	89	7194	7305	
4184	4214	89	90	7305	7415	
4214	4245	90	91	7415	7529	
4245	4276	91	92	7529	7643	
4276	4307	92	93	7643	7757	
4307	4338	93	94	7757	7872	
4338	4369	94	95	7872	7986	
4369	4401	95	96	7986	8104	
4401	4433	96	97	8104	8221	
4433	4465	97	98	8221	8339	
4465	4497	98	99	8339	8457	
4497	4530	99	100	8457	8578	

CCT (When CCT Range Selector @ 2200K - 20000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
4530	4563	100	101	8578	8700	
4563	4596	101	102	8700	8821	
4596	4629	102	103	8821	8943	
4629	4663	103	104	8943	9068	
4663	4696	104	105	9068	9190	
4696	4730	105	106	9190	9315	
4730	4765	106	107	9315	9444	
4765	4799	107	108	9444	9569	
4799	4834	108	109	9569	9698	
4834	4869	109	110	9698	9827	
4869	4904	110	111	9827	9955	
4904	4940	111	112	9955	10088	
4940	4976	112	113	10088	10221	
4976	5012	113	114	10221	10353	
5012	5048	114	115	10353	10486	
5048	5085	115	116	10486	10622	
5085	5122	116	117	10622	10758	
5122	5159	117	118	10758	10894	
5159	5196	118	119	10894	11030	
5196	5234	119	120	11030	11170	
5234	5272	120	121	11170	11310	
5272	5310	121	122	11310	11450	
5310	5348	122	123	11450	11590	
5348	5387	123	124	11590	11734	
5387	5426	124	125	11734	11877	
5426	5466	125	126	11877	12025	
5466	5505	126	127	12025	12168	
5505	5545	127	128	12168	12315	
5545	5585	128	129	12315	12463	
5585	5626	129	130	12463	12614	
5626	5667	130	131	12614	12765	
5667	5708	131	132	12765	12916	
5708	5749	132	133	12916	13067	
5749	5791	133	134	13067	13221	
5791	5833	134	135	13221	13376	
5833	5875	135	136	13376	13530	
5875	5917	136	137	13530	13685	
5917	5960	137	138	13685	13843	
5960	6004	138	139	13843	14005	
6004	6047	139	140	14005	14164	
6047	6091	140	141	14164	14326	
6091	6135	141	142	14326	14488	
6135	6180	142	143	14488	14653	
6180	6224	143	144	14653	14815	
6224	6269	144	145	14815	14981	
6269	6315	145	146	14981	15150	
6315	6361	146	147	15150	15320	
6361	6407	147	148	15320	15489	
6407	6453	148	149	15489	15658	
6453	6500	149	150	15658	15831	

CCT (When CCT Range Selector @ 2200K - 20000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
6500	6570	150	151	15831	16089	
6570	6641	151	152	16089	16351	
6641	6712	152	153	16351	16612	
6712	6784	153	154	16612	16877	
6784	6857	154	155	16877	17146	
6857	6931	155	156	17146	17418	
6931	7006	156	157	17418	17694	
7006	7081	157	158	17694	17971	
7081	7157	158	159	17971	18250	
7157	7234	159	160	18250	18534	
7234	7312	160	161	18534	18821	
7312	7391	161	162	18821	19112	
7391	7470	162	163	19112	19403	
7470	7551	163	164	19403	19701	
7551	7632	164	165	19701	19999	
7632	7714	165	166	19999	20301	
7714	7797	166	167	20301	20607	
7797	7881	167	168	20607	20916	
7881	7966	168	169	20916	21229	
7966	8052	169	170	21229	21546	
8052	8138	170	171	21546	21862	
8138	8226	171	172	21862	22186	
8226	8314	172	173	22186	22510	
8314	8404	173	174	22510	22842	
8404	8494	174	175	22842	23173	
8494	8586	175	176	23173	23512	
8586	8678	176	177	23512	23850	
8678	8772	177	178	23850	24196	
8772	8866	178	179	24196	24542	
8866	8961	179	180	24542	24892	
8961	9058	180	181	24892	25249	
9058	9155	181	182	25249	25607	
9155	9254	182	183	25607	25971	
9254	9353	183	184	25971	26335	
9353	9454	184	185	26335	26707	
9454	9556	185	186	26707	27083	
9556	9659	186	187	27083	27462	
9659	9763	187	188	27462	27845	
9763	9868	188	189	27845	28232	
9868	9974	189	190	28232	28622	
9974	10081	190	191	28622	29016	
10081	10190	191	192	29016	29417	
10190	10299	192	193	29417	29818	
10299	10410	193	194	29818	30227	
10410	10522	194	195	30227	30639	
10522	10635	195	196	30639	31055	
10635	10750	196	197	31055	31479	
10750	10866	197	198	31479	31906	
10866	10982	198	199	31906	32333	
10982	11101	199	200	32333	32771	

CCT (When CCT Range Selector @ 2200K - 20000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
11101	11220	200	201	32771	33209	
11220	11341	201	202	33209	33655	
11341	11463	202	203	33655	34104	
11463	11586	203	204	34104	34557	
11586	11711	204	205	34557	35017	
11711	11837	205	206	35017	35481	
11837	11964	206	207	35481	35949	
11964	12093	207	208	35949	36423	
12093	12223	208	209	36423	36902	
12223	12355	209	210	36902	37388	
12355	12488	210	211	37388	37878	
12488	12622	211	212	37878	38371	
12622	12758	212	213	38371	38872	
12758	12895	213	214	38872	39376	
12895	13034	214	215	39376	39888	
13034	13174	215	216	39888	40403	
13174	13316	216	217	40403	40926	
13316	13459	217	218	40926	41453	
13459	13604	218	219	41453	41987	
13604	13751	219	220	41987	42528	
13751	13899	220	221	42528	43073	
13899	14048	221	222	43073	43621	
14048	14199	222	223	43621	44177	
14199	14352	223	224	44177	44741	
14352	14507	224	225	44741	45311	
14507	14663	225	226	45311	45886	
14663	14821	226	227	45886	46467	
14821	14980	227	228	46467	47053	
14980	15141	228	229	47053	47645	
15141	15304	229	230	47645	48246	
15304	15469	230	231	48246	48853	
15469	15635	231	232	48853	49464	
15635	15804	232	233	49464	50086	
15804	15974	233	234	50086	50712	
15974	16146	234	235	50712	51346	
16146	16319	235	236	51346	51983	
16319	16495	236	237	51983	52630	
16495	16673	237	238	52630	53286	
16673	16852	238	239	53286	53945	
16852	17033	239	240	53945	54611	
17033	17217	240	241	54611	55289	
17217	17402	241	242	55289	55970	
17402	17589	242	243	55970	56658	
17589	17778	243	244	56658	57354	
17778	17970	244	245	57354	58061	
17970	18163	245	246	58061	58772	
18163	18359	246	247	58772	59493	
18359	18556	247	248	59493	60219	
18556	18756	248	249	60219	60955	
18756	18958	249	250	60955	61699	

CCT (When CCT Range Selector @ 2200K - 20000K)

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
18958	19162	250	251	61699	62450	
19162	19368	251	252	62450	63208	
19368	19576	252	253	63208	63974	
19576	19787	253	254	63974	64751	
19787	20000	254	255	64751	65535	

Green Magenta Poin Channel (GMP)

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Neutral / No Effect	0	1	-	-	Default @ 128 (8bit) / 32768 (16bit)
Full Minus Green	2	3	-	-	
-99% to -1%	4	126	-	-	
Neutral / No Effect	127	128	-	-	- 0,025
1% to 99%	129	253	-	-	
Full Plus Green	254	255	-	-	

Crossfade from CCT to RGB

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Crossfade from CCT to RGB	0	255	0	65535	Default @ 0 Linear Crossfade from CCT to RGB

Red

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Red	0	255	0	65535	Default @ 255 (8bit) / 65535 (16bit)

Green

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Green	0	255	0	65535	Default @ 255 (8bit) / 65535 (16bit)

Blue

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Blue	0	255	0	65535	Default @ 255 (8bit) / 65535 (16bit)

PC Amber

Function	8 bit value		16 bit value		Note
	From	To	From	To	
PC Amber	0	255	0	65535	Default @ 255 (8bit) / 65535 (16bit)

Mint

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Mint	0	255	0	65535	Default @ 255 (8bit) / 65535 (16bit)

Royal Blue

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Royal Blue	0	255	0	65535	Default @ 255 (8bit) / 65535 (16bit)

White Point Selector

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Default	0	1	0	511	Default @ 0, From Color Space Definition on the device
Dynamic	2	255	512	65535	2800K - 10000K

Dynamic White Point 2800K - 10000K

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
2800	2900	2	6	512	1415	Default @ 0
2900	3000	6	9	1415	2318	
3000	3100	9	13	2318	3221	
3100	3200	13	16	3221	4124	
3200	3300	16	20	4124	5027	
3300	3400	20	23	5027	5931	
3400	3500	23	27	5931	6834	
3500	3600	27	30	6834	7737	
3600	3700	30	34	7737	8640	
3700	3800	34	37	8640	9543	
3800	3900	37	41	9543	10446	
3900	4000	41	44	10446	11349	
4000	4100	44	48	11349	12252	
4100	4200	48	51	12252	13155	
4200	4300	51	55	13155	14058	
4300	4400	55	58	14058	14962	
4400	4500	58	62	14962	15865	
4500	4600	62	65	15865	16768	
4600	4700	65	69	16768	17671	
4700	4800	69	72	17671	18574	
4800	4900	72	76	18574	19477	
4900	5000	76	79	19477	20380	
5000	5100	79	83	20380	21283	
5100	5200	83	86	21283	22186	
5200	5300	86	90	22186	23089	
5300	5400	90	93	23089	23993	
5400	5500	93	97	23993	24896	
5500	5600	97	100	24896	25799	
5600	5700	100	104	25799	26702	
5700	5800	104	107	26702	27605	

Dynamic White Point 2800K - 10000K

Function		8 bit value		16 bit value		Note
CCT(K) From	CCT(K) To	From	To	From	To	
5800	5900	107	111	27605	28508	
5900	6000	111	114	28508	29411	
6000	6100	114	118	29411	30314	
6100	6200	118	121	30314	31217	
6200	6300	121	125	31217	32120	
6300	6400	125	129	32120	33024	
6400	6500	129	132	33024	33927	
6500	6600	132	136	33927	34830	
6600	6700	136	139	34830	35733	
6700	6800	139	143	35733	36636	
6800	6900	143	146	36636	37539	
6900	7000	146	150	37539	38442	
7000	7100	150	153	38442	39345	
7100	7200	153	157	39345	40248	
7200	7300	157	160	40248	41151	
7300	7400	160	164	41151	42054	
7400	7500	164	167	42054	42958	
7500	7600	167	171	42958	43861	
7600	7700	171	174	43861	44764	
7700	7800	174	178	44764	45667	
7800	7900	178	181	45667	46570	
7900	8000	181	185	46570	47473	
8000	8100	185	188	47473	48376	
8100	8200	188	192	48376	49279	
8200	8300	192	195	49279	50182	
8300	8400	195	199	50182	51085	
8400	8500	199	202	51085	51989	
8500	8600	202	206	51989	52892	
8600	8700	206	209	52892	53795	
8700	8800	209	213	53795	54698	
8800	8900	213	216	54698	55601	
8900	9000	216	220	55601	56504	
9000	9100	220	223	56504	57407	
9100	9200	223	227	57407	58310	
9200	9300	227	230	58310	59213	
9300	9400	230	234	59213	60116	
9400	9500	234	237	60116	61020	
9500	9600	237	241	61020	61923	
9600	9700	241	244	61923	62826	
9700	9800	244	248	62826	63729	
9800	9900	248	251	63729	64632	
9900	10000	251	255	64632	65535	

Crossfade from RGB to GEL

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Crossfade from RGB to GEL	0	255	0	65535	Default @ 0 Linear Crossfade from RGB to GEL

Gel Source Lamp CCT

Function	8 bit value		16 bit value		Note
	From	To	From	To	
2700K	0	9	-	-	Default @ 0
2800K	10	19	-	-	
3000K	20	29	-	-	
3200K	30	39	-	-	
4000K	40	49	-	-	
5000K	50	59	-	-	
5600K	60	69	-	-	
6500K	70	79	-	-	
Blackout	80	89	-	-	
Reserved	90	255	-	-	

GEL Brand / Category Selector

Function	8 bit value		16 bit value		Note
	From	To	From	To	
LEE: Color correction	0	9	-	-	Default @ 0
LEE: Color Filters	10	19	-	-	
LEE: 600 Series	20	29	-	-	
LEE: Cosmetic Filters	30	39	-	-	
LEE: 700 Series	40	49	-	-	
RC: Color correction	50	59	-	-	
RC: CalC	60	69	-	-	
RC: StSelection	70	79	-	-	
RC: C-Lux	80	89	-	-	
Blackout	90	99	-	-	
Reserved	100	255	-	-	

Category | Lee: Color Correction

Function Gel Name	8 bit value		Gel #
	From	To	
Double CTB	0	1	200
Full CTB	2	3	201
3/4 CTB	4	5	281
1/2 CTB	6	7	202
1/4 CTB	8	9	203
1/8 CTB	10	11	218
Double CTO	12	13	287
Full CTO	14	15	204
3/4 CTO	16	17	285
1/2 CTO	18	19	205
1/4 CTO	20	21	206
1/8 CTO	22	23	223
1 1/2 CTB	24	25	283
1 1/2 CTO	26	27	286
Full CTS	28	29	441
1/2 CTS	30	31	442
1/4 CTS	32	33	443
1/8 CTS	34	35	444
Full CTO + .3 ND	36	37	207
Full CTO + .6 ND	38	39	208
L.C.T. Yellow (Y1)	40	41	212
White Flame Green	42	43	213
LEE Fluorescent Green	44	45	219
Super Correction L.C.T. Yellow	46	47	230
Super Correction W.F. Green	48	49	232
H.M.I. (to Tungsten)	50	51	236
C.I.D. (to Tungsten)	52	53	237
C.S.I. (to Tungsten)	54	55	238
LEE Fluorescent 5700 Kelvin	56	57	241
LEE Fluorescent 4300 Kelvin	58	59	242
LEE Fluorescent 3600 Kelvin	60	61	243
LEE Plus Green	62	63	244
1/2 Plus Green	64	65	245
1/4 Plus Green	66	67	246
1/8 Plus Green	68	69	278
Lee Minus Green	70	71	247
1/2 Minus Green	72	73	248
1/4 Minus Green	74	75	249
1/8 Minus Green	76	77	279
Blackout	78	79	-
Reserved	80	255	-

Category | Lee: Color Filters

Function Gel Name	8 bit value		Gel #
	From	To	
Rose Pink	0	1	2
Lavender Tint	2	3	3
Medium Bastard Amber	4	5	4
Pale Yellow	6	7	7
Dark Salmon	8	9	8
Pale Amber Gold	10	11	9
Medium Yellow	12	13	10
Straw Tint	14	15	13
Surprise Peach	16	17	17
Fire	18	19	19
Medium Amber	20	21	20
Gold Amber	22	23	21
Dark Amber	24	25	22
Scarlet	26	27	24
Sunset Red	28	29	25
Bright Red	30	31	26
Light Pink	32	33	35
Medium Pink	34	35	36
Dark Magenta	36	37	46
Rose Purple	38	39	48
Light Lavender	40	41	52
Paler Lavender	42	43	53
Lavender	44	45	58
Mist Blue	46	47	61
Pale Blue	48	49	63
Sky Blue	50	51	68
Evening Blue	52	53	75
Just Blue	54	55	79
Deeper Blue	56	57	85
Lime Green	58	59	88
Moss Green	60	61	89
Dark Yellow Green	62	63	90
Spring Yellow	64	65	100
Yellow	66	67	101
Light Amber	68	69	102
Straw	70	71	103
Deep Amber	72	73	104
Primary Red	74	75	106
Light Rose	76	77	107
English Rose	78	79	108
Light Salmon	80	81	109
Middle Rose	82	83	110
Dark Pink	84	85	111
Magenta	86	87	113
Peacock Blue	88	89	115
Steel Blue	90	91	117
Light Blue	92	93	118
Deep Blue	94	95	120
LEE Green	96	97	121
Fern Green	98	99	122
Dark Green	100	101	124

Category | Lee: Color Filters

Function Gel Name	8 bit value		Gel #
	From	To	
Smokey Pink	102	103	127
Bright Pink	104	105	128
Marine Blue	106	107	131
Golden Amber	108	109	134
Deep Golden Amber	110	111	135
Pale Lavender	112	113	136
Special Lavender	114	115	137
Pale Green	116	117	138
Summer Blue	118	119	140
Pale Violet	120	121	142
Pale Navy Blue	122	123	143
No Color Blue	124	125	144
Apricot	126	127	147
Bright Rose	128	129	148
Gold Tint	130	131	151
Pale Gold	132	133	152
Pale Salmon	134	135	153
Pale Rose	136	137	154
Chocolate	138	139	156
Pink	140	141	157
No Color Straw	142	143	159
Slate Blue	144	145	161
Bastard Amber	146	147	162
Flame Red	148	149	164
Daylight Blue	150	151	165
Lilac Tint	152	153	169
Deep Lavender	154	155	170
Dark Steel Blue	156	157	174
Loving Amber	158	159	176
Dark Lavender	160	161	180
Light Red	162	163	182
Flesh Pink	164	165	192
Surprise Pink	166	167	194
Zenith Blue	168	169	195
True Blue	170	171	196
Alice Blue	172	173	197
Palace Blue	174	175	198
Regal Blue	176	177	199
Blackout	178	179	-
Reserved	180	255	-

Category | Lee: 600 Series

Function	8 bit value		Gel #
Gel Name	From	To	
Arctic White	0	1	600
Silver	2	3	601
Platinum	4	5	602
Moonlight White	6	7	603
Full CT 85	8	9	604
Industry Sodium	10	11	650
HI Sodium	12	13	651
Urban Sodium	14	15	652
LO Sodium	16	17	653
Blackout	18	19	-
Reserved	20	255	-

Category | Lee: Cosmetic Filters

Function	8 bit value		Gel #
Gel Name	From	To	
Cosmetic Peach	0	1	184
Cosmetic Silver Rose	2	3	186
Cosmetic Rouge	4	5	187
Cosmetic Highlight	6	7	188
Cosmetic Silver Moss	8	9	189
Cosmetic Aqua Blue	10	11	191
Lily Frost	12	13	705
Shanklin Frost	14	15	717
Half Shanklin Frost	16	17	718
Durham Daylight Frost	18	19	720
Hampshire Rose	20	21	749
Soft Amber Key 1	22	23	774
Soft Amber Key 2	24	25	775
Moroccan Frost	26	27	791
Blue Diffusion	28	29	217
Blue Frost	30	31	221
Daylight Blue Frost	32	33	224
Blackout	34	35	-
Reserved	36	255	-

Category | Lee: 700 Series

Function Gel Name	8 bit value		Gel #
	From	To	
Perfect Lavender	0	1	700
Provence	2	3	701
Special Pale Lavender	4	5	702
Cold Lavender	6	7	703
Lily	8	9	704
King Fals Lavender	10	11	706
Cool Lavender	12	13	708
Electric Lilac	14	15	709
Spir Special Blue	16	17	710
Cold Blue	18	19	711
Bedford Blue	20	21	712
Elysian Blue	22	23	714
Cabana Blue	24	25	715
Mikkel Blue	26	27	716
Colour Wash Blue	28	29	719
Berry Blue	30	31	721
Virgin Blue	32	33	723
Ocean Blue	34	35	724
Old Steel Blue	36	37	725
Steel Green	38	39	728
Liberty Green	40	41	730
Dirty Ice	42	43	731
Damp Squib	44	45	733
JAS Green	46	47	738
Bram Brown	48	49	742
Dirty White	50	51	744
Brown	52	53	746
Easy White	54	55	747
Seedy Pink	56	57	748
Wheat	58	59	763
Sun Colour Straw	60	61	764
LEE Yellow	62	63	765
Cardbox Amber	64	65	773
Nectarine	66	67	776
Millenium Gold	68	69	778
Bastard Pink	70	71	779
Terry Red	72	73	781
Blood Red	74	75	789
Moroccan Pink	76	77	790
Pretty n'Pink	78	79	794
Magical Magenta	80	81	795
Blackout	82	83	-
Reserved	84	255	-

Category | Rc: Color Correction

Function Gel Name	8 bit value		Gel #
	From	To	
Full CTB	0	1	3202
3/4 CTB	2	3	3203
1/2 CTB	4	5	3204
1/3 CTB	6	7	3206
1/4 CTB	8	9	3208
1/8 CTB	10	11	3216
Double CTB	12	13	3220
Full CTO	14	15	3407
3/4 CTO	16	17	3411
1/2 CTO	18	19	3408
1/4 CTO	20	21	3409
1/8 CTO	22	23	3410
Double CTO	24	25	3420
Full CTS	26	27	3441
1/2 CTS	28	29	3442
1/4 CTS	30	31	3443
1/8 CTS	32	33	3444
Full Plusgreen	34	35	3304
1/2 Plusgreen	36	37	3315
1/4 Plusgreen	38	39	3316
1/8 Plusgreen	40	41	3317
Full Minusgreen	42	43	3308
3/4 Minusgreen	44	45	3309
1/2 Minusgreen	46	47	3313
1/4 Minusgreen	48	49	3314
1/8 Minusgreen	50	51	3318
Fluorofilter	52	53	3310
Industrial Vapor	54	55	3150
Urban Vapor	56	57	3152
Tough Y-1	58	59	3107
Tough MT 54	60	61	3134
Tough MTY	62	63	3106
Tough MT2	64	65	3102
Blackout	66	67	-
Reserved	68	255	-

Category | Rc: CalC

Function	8 bit value		Gel #
Gel Name	From	To	
15 Blue	0	1	4215
30 Blue	2	3	4230
60 Blue	4	5	4260
90 Blue	6	7	4290
7 Cyan	8	9	4307
15 Cyan	10	11	4315
30 Cyan	12	13	4330
60 Cyan	14	15	4360
90 Cyan	16	17	4390
15 Green	18	19	4415
30 Green	20	21	4430
60 Green	22	23	4460
90 Green	24	25	4490
15 Yellow	26	27	4515
30 Yellow	28	29	4530
60 Yellow	30	31	4560
90 Yellow	32	33	4590
15 Red	34	35	4615
30 Red	36	37	4630
60 Red	38	39	4660
90 Red	40	41	4690
15 Magenta	42	43	4715
30 Magenta	44	45	4730
60 Magenta	46	47	4760
90 Magenta	48	49	4790
15 Pink	50	51	4815
30 Pink	52	53	4830
60 Pink	54	55	4860
90 Pink	56	57	4890
15 Lavender	58	59	4915
30 Lavender	60	61	4930
60 Lavender	62	63	4960
90 Lavender	64	65	4990
Blackout	66	67	-
Reserved	68	255	-

Category | Rc: StSelection

Function	8 bit value		Gel #
Gel Name	From	To	
VS Red	0	1	2001
VS Orange	2	3	2002
VS Yellow	4	5	2003
VS Green	6	7	2004
VS Cyan	8	9	2005
VS Azure	10	11	2006
VS Blue	12	13	2007
VS Indigo	14	15	2008
VS Violet	16	17	2009
VS Magenta	18	19	2010
Blackout	20	21	-
Reserved	22	255	-

Category | Rc: C-Lux

Function	8 bit value		Gel #
Gel Name	From	To	
Bastard Amber	0	1	2
Pale Bastard Amber	2	3	302
No Color Straw	4	5	6
Pale Gold	6	7	8
Daffodil	8	9	310
Straw	10	11	12
Light Amber	12	13	16
Gallo Gold	14	15	316
Light Flame	16	17	17
Flame	18	19	18
Mayan Sun	20	21	318
Golden Amber	22	23	21
Soft Golden Amber	24	25	321
Orange	26	27	23
Henny Sky	28	29	325
Light Red	30	31	26
No Color Pink	32	33	33
Blush Pink	34	35	333
Flesh Pink	36	37	34
Pale Rose Pink	38	39	37
Salmon	40	41	41
Deep Salmon	42	43	42
Middle Rose	44	45	44
Light Rose Purple	46	47	47
Surprise Pink	48	49	51
No Color Blue	50	51	60
Clearwater	52	53	360
Booster Blue	54	55	62
Tipton Blue	56	57	362
Blue Bell	58	59	364
Daylight Blue	60	61	65
Tharon Delft Blue	62	63	365
Cerulean Blue	64	65	375
Bermuda Blue	66	67	376
Green Blue	68	69	77
Alice Blue	70	71	378
Primary Blue	72	73	80
Baldassari Blue	74	75	381
Medium Blue	76	77	83
Pale Yellow Green	78	79	87
Light Green	80	81	88
Moss Green	82	83	89
Primary Green	84	85	91
Turquoise	86	87	92
Blue Green	88	89	93
Chocolate	90	91	99
Blackout	92	93	-
Reserved	94	255	-

Transition Type Channel

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Direct XY (Constant Brightness)	0	9	-	-	Direct fades linear on the shortest distance
Standard Direct XY (w/o Constant Brightness)	10	19	-	-	Direct fades linear on the shortest distance
Through Black	20	29	-	-	"Through Black" fades from color 1 to black to color 2.
Through White 3200K (w/o Constant Brightness)	30	39	-	-	"Through White" fades from color 1 to white to color 2.
Through White 3200K (Constant Brightness)	40	49	-	-	"Through White" fades from color 1 to white to color 2.
Through White 5600K (w/o Constant Brightness)	50	59	-	-	"Through White" fades from color 1 to white to color 2.
Through White 5600K (Constant Brightness)	60	69	-	-	"Through White" fades from color 1 to white to color 2.
Through White 6500K (w/o Constant Brightness)	70	79	-	-	"Through White" fades from color 1 to white to color 2.
Through White 6500K (Constant Brightness)	80	89	-	-	"Through White" fades from color 1 to white to color 2.
Reserved	90	255	-	-	-

Strobe

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Open	0	1	0	257	Default @ 0
0,9 Hz to 20 Hz Strobging Duty Cycle Open Time: 100 ms to 25 ms Duty Cycle Closed Time: 1000 ms to 25 ms	2	62	514	15934	
Open	63	64	15935	16704	
0,8 Hz to 6,6 Hz Pulse-In Strobging Duty Cycle Puls-In Time: 250 ms to 50 ms Duty Cycle Closed Time: 1000 ms to 100 ms	65	125	16705	32125	
Open	126	127	32126	32895	
0,8 Hz to 6,6 Hz Pulse-Out Strobging Duty Cycle Puls-Out Time: 250 ms to 50 ms Duty Cycle Closed Time: 1000 ms to 100 ms	128	188	32896	48316	
Open	189	190	48317	49086	
0,9 Hz to 20 Hz Random Strobging Duty Cycle Open Time: 100 ms to 25 ms Duty Cycle Closed Time: 1000 ±500 ms to 25 ±12 ms	191	251	49087	64507	
Open	252	255	64508	65535	

Gobo Rotation

Function	8 bit value		Note
	From	To	
Gobo Index 0° to 360°	0	127	Default @ 0
CW rotation - 40 rpm to 0,10 rpm	128	190	
Stop	191	192	
CCW Rotation - 0,10 rpm to 40 rpm	193	255	

Preset Channel

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Safe					
No Function	0	1	-	-	Default @ 0
User Defined Presets					
Preset 01	2	3	-	-	Preset saved by user
Preset 02	4	5	-	-	
Preset 03	6	7	-	-	
Preset 04	8	9	-	-	
Preset 05	10	11	-	-	
Preset 06	12	13	-	-	
Preset 07	14	15	-	-	
Preset 08	16	17	-	-	
Preset 09	18	19	-	-	
Preset 10	20	21	-	-	
Preset 11	22	23	-	-	
Preset 12	24	25	-	-	
Preset 13	26	27	-	-	
Preset 14	28	29	-	-	
Preset 15	30	31	-	-	
Preset 16	32	33	-	-	
Preset 17	34	35	-	-	
Preset 18	36	37	-	-	
Preset 19	38	39	-	-	
Preset 20	40	41	-	-	
Reserved	42	167	-	-	
Factory Presets					
Preset 01	168	169	-	-	CCT - 2000K (+/- 0 GN)
Preset 02	170	171	-	-	CCT - 2500K (+/- 0 GN)
Preset 03	172	173	-	-	CCT - 2900K (+/- 0 GN)
Preset 04	174	175	-	-	CCT - 3200K (+/- 0 GN)
Preset 05	176	177	-	-	CCT - 4000K (+/- 0 GN)
Preset 06	178	179	-	-	CCT - 5000K (+/- 0 GN)
Preset 07	180	181	-	-	CCT - 5600K (+/- 0 GN)
Preset 08	182	183	-	-	CCT - 6500K (+/- 0 GN)
Preset 09	184	185	-	-	CCT - 8000K (+/- 0 GN)
Preset 10	186	187	-	-	CCT - 10000K (+/- 0 GN)
Reserved	188	207	-	-	-
Preset 21	208	209	-	-	HSI - 120° Hue, 100% Saturation
Preset 22	210	211	-	-	HSI - 240° Hue, 100% Saturation
Preset 23	212	213	-	-	GEL - RC 3408, Base CCT 5600K
Preset 24	214	215	-	-	GEL - Lee 187, Base CCT 3200K
Preset 25	216	217	-	-	GEL - RC 3152, Base CCT 3200K
Preset 26	218	219	-	-	GEL - Lee 162, Base CCT 3200K
Reserved	220	255	-	-	-

Fan Control Channel

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Safe					
No Function	0	1	-	-	Use Fan Mode Setting of Fixture Menu
Auto	2	3	-	-	Automatically regulates fan speed - Drops light only if passing the thermal protection treshold.
Turbo	4	5	-	-	Fixed - 100%
Fan Speed	6	107	-	-	Manual Fan Speed: 0% at 6 dmx value - 20% to 100% from 7 to 107 dmx value in linear progression
Dynamic Light Output					
Quiet 1 DLO	108	109	-	-	Fixed Fan Speed (50%)
Quiet 2 DLO	110	111	-	-	Fixed Fan Speed (35%)
Off DLO	112	113	-	-	Fixed Fan Speed (0%)
Constant Light Output					
Quiet 1 CLO	114	115	-	-	Fixed Fan Speed (50%)
Quiet 2 CLO	116	117	-	-	Fixed Fan Speed (35%)
Off CLO	118	119	-	-	Fixed Fan Speed (0%)
Reserved	120	255	-	-	---

Control Channel

Function	8 bit value		Note
	From	To	
No Function / Safe	0	1	Default @ 0 Hold 3s to take function
Dimmer Speed Auto	2	3	
Dimmer Speed Fast	4	5	
Dimmer Speed Medium	6	7	
Dimmer Speed Slow	8	9	
Dimmer Speed Off	10	11	
Dimmer Curve Linear	12	13	
Dimmer Curve S-Curve	14	15	
Dimmer Curve Square Law	16	17	
Dimmer Curve Inv. Square Law	18	19	
Dimmer Curve High Res @ Low	20	21	
Dimmer Curve Tungsten	22	23	
Tungsten Emulation On	24	25	
Tungsten Emulation Off	26	27	
Dimmer End Fade Off	28	29	
Dimmer End Snap Off	30	31	
Color Space Native	32	33	
Color Space ProPhoto	34	35	
Color Space sRGB	36	37	
Color Space Rec. 2020	38	39	
Color Space Rec. 709	40	41	
Led Mode High Brightness	42	43	
Led Mode High Quality	44	45	
Fan Mode Auto	46	47	
Fan Mode Turbo	48	49	
Fan Mode Manual	50	51	
Fan Mode Quiet 1 DLO	52	53	
Fan Mode Quiet 2 DLO	54	55	
Fan Mode Off DLO	56	57	

Control Channel

Function	8 bit value		Note
	From	To	
Fan Mode Quiet 1 CLO	58	59	
Fan Mode Quiet 2 CLO	60	61	
Fan Mode Off CLO	62	63	
Signal Fault Hold	64	65	
Signal Fault Hold - On Encoder Touch CCT mode	66	67	
Signal Fault Hold - On Encoder Touch RGB mode	68	69	
Signal Fault Hold - On Encoder Touch HSI mode	70	71	
Signal Fault Hold - On Encoder Touch XY mode	72	73	
Signal Fault Hold - On Encoder Touch GEL mode	74	75	
Reserved	76	77	
Signal Fault Standalone	78	79	
Signal Fault Blackout	80	81	
Signal Fault Emergency	82	83	
Startup Behaviour On Encoder Touch - CCT mode	84	85	
Startup Behaviour On Encoder Touch - RGB mode	86	87	
Startup Behaviour On Encoder Touch - HSI mode	88	89	
Startup Behaviour On Encoder Touch - XY mode	90	91	
Startup Behaviour On Encoder Touch - GEL mode	92	93	
Reserved	94	95	
Startup Behaviour Standalone	96	97	
Startup Behaviour Blackout	98	99	
Startup Behaviour Emergency	100	101	
Led Frequency 1282Hz	102	103	
Led Frequency 2000Hz	104	105	
Led Frequency 4000Hz	106	107	
Led Frequency 6000Hz	108	109	
Led Frequency 10kHz	110	111	
Led Frequency 12kHz	112	113	
Led Frequency 15kHz	114	115	
Led Frequency 20kHz	116	117	
Led Frequency 25kHz	118	119	
Led Frequency 36kHz	120	121	
Led Frequency 40kHz	122	123	
Power Limit 100%	124	125	
Power Limit 75%	126	127	
Power Limit 50%	128	129	
Power Limit 25%	130	131	
Reserved	132	135	
Backlight Timeout Always On	136	137	
Backlight Timeout 10s	138	139	
Backlight Timeout 30s	140	141	
Backlight Timeout 60s	142	143	
Backlight Display 25%	144	145	
Backlight Display 50%	146	147	
Backlight Display 75%	148	149	
Backlight Display 100%	150	151	
Backlight Encoder Off	152	153	
Backlight Encoder On	154	155	
Flip Display On	156	157	
Flip Display Off	158	159	
Keylock On	160	161	

Control Channel

Function	8 bit value		Note
	From	To	
Keylock Off	162	163	
Stand Alone Master DMX	164	165	
Stand Alone Master NO DMX	166	167	
Stand Alone Slave	168	169	
Stand Alone CCT Mode	170	171	
Stand Alone RGB Mode	172	173	
Stand Alone HSI Mode	174	175	
Stand Alone XY Mode	176	177	
Stand Alone Gel Mode	178	179	
Reserved	180	181	
Stand Alone Preset Mode 1	182	183	
Stand Alone Preset Mode 2	184	185	
Stand Alone Preset Mode 3	186	187	
Stand Alone Preset Mode 4	188	189	
Stand Alone Preset Mode 5	190	191	
Stand Alone Preset Mode 6	192	193	
Stand Alone Preset Mode 7	194	195	
Stand Alone Preset Mode 8	196	197	
Stand Alone Preset Mode 9	198	199	
Stand Alone Preset Mode 10	200	201	
Stand Alone Preset Mode 11	202	203	
Stand Alone Preset Mode 12	204	205	
Stand Alone Preset Mode 13	206	207	
Stand Alone Preset Mode 14	208	209	
Stand Alone Preset Mode 15	210	211	
Stand Alone Preset Mode 16	212	213	
Stand Alone Preset Mode 17	214	215	
Stand Alone Preset Mode 18	216	217	
Stand Alone Preset Mode 19	218	219	
Stand Alone Preset Mode 20	220	221	
Configuration Presets Preset 1	222	223	
Configuration Presets Preset 2	224	225	
Configuration Presets Preset 3	226	227	
Configuration Presets Preset 4	228	229	
Dimmer Minimum End Standard	230	231	
Dimmer Minimum End Low	232	233	
Spektra Calibration ON	234	235	
Spektra Calibration PURE COLORS	236	237	
Spektra Calibration OFF	238	239	
Reserved	240	241	
Gobo Rotator OFF	242	243	
Gobo Rotator ON	244	245	
Gobo Reset	246	247	
Reserved	248	251	
Factory Default of control functions	252	253	
Reserved	254	255	

Color Correction Mode Selector

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Standard	0	9	-	-	Default @ 0 Color correction occurs with a purely mathematical shift of the xy coordinates
Subtractive Color	10	19	-	-	Color correction occurs by acting on the emitter (i.e. the LED source)
Reserved	20	255	-	-	

Cooler / Warmer

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Cooler/Warmer	0	255	-	-	Default @ 128 Linear Correction from Cooler to Warmer

Desaturate / Saturate

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Desaturate/Saturate	0	255	-	-	Default @ 128 Linear change from a less saturated light to a more saturated light

CC Parameter 1

Function	8 bit value		16 bit value		Note
	From	To	From	To	

Color Correction: Standard Mode

±Red	0	255	-	-	Default @ 128 Linear change from less Red to more Red as you move through x-y coordinates
------	---	-----	---	---	--

Color Correction: Subtractive Color Mode

±Red	0	255	-	-	Default @ 128 Linear change from less red to more red by varying the emission of the Red LEDs
------	---	-----	---	---	--

CC Parameter 2

Function	8 bit value		16 bit value		Note
	From	To	From	To	

Color Correction: Standard Mode

±Green	0	255	-	-	Default @ 128 Linear change from less Green to more Green as you move through x-y coordinates
--------	---	-----	---	---	--

Color Correction: Subtractive Color Mode

±Green	0	255	-	-	Default @ 128 Linear change from less red to more red by varying the emission of the Green LEDs
--------	---	-----	---	---	--

CC Parameter 3

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Color Correction: Standard Mode					
±Blue	0	255	-	-	Default @ 128 Linear change from less Blue to more Blue as you move through x-y coordinates
Color Correction: Subtractive Color Mode					
±Blue	0	255	-	-	Default @ 128 Linear change from less red to more red by varying the emission of the Blue LEDs

CC Parameter 4

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Color Correction: Standard Mode					
±Cyan	0	255	-	-	Default @ 128 Linear change from less Cyan to more Cyan as you move through x-y coordinates
Color Correction: Subtractive Color Mode					
±PC Amber	0	255	-	-	Default @ 128 Linear change from less red to more red by varying the emission of the PC Amber LEDs

CC Parameter 5

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Color Correction: Standard Mode					
±Magenta	0	255	-	-	Default @ 128 Linear change from less Magenta to more Magenta as you move through x-y coordinates
Color Correction: Subtractive Color Mode					
±Mint	0	255	-	-	Default @ 128 Linear change from less red to more red by varying the emission of the Mint LEDs

CC Parameter 6

Function	8 bit value		16 bit value		Note
	From	To	From	To	
Color Correction: Standard Mode					
±Yellow	0	255	-	-	Default @ 128 Linear change from less Yellow to more Yellow as you move through x-y coordinates
Color Correction: Subtractive Color Mode					
±Royal Blue	0	255	-	-	Default @ 128 Linear change from less red to more red by varying the emission of the Royal Blue LEDs